



MEMO POWER SERIES

6~10KVA

BI-Phases PF=0.9 (PF=1.0 optional)

Features

- N+X parallel redundancy
- Online double conversion with DSP control
- Input current harmonic: <3%
- Optimization battery group, the quantity Of battery:
16 / 18 / 20pcs optional
- High output power factor at PF0.9
- Wide input voltage range: 72 - 159vac
- Wide input frequency range $50 \pm 10\%$ or $60 \pm 10\%$ Hz
- Support generator input
- Support economic (ECO) operation mode
- Self - testing when startup
- Options: SNMP card / dry contact card / parallel card.
- Cold start



Control Panel

Technical Specifications:

Model	MEMO S/H 6KVA		MEMO S/H 10KVA
Capacity	6KVA / 5.4KW		10KVA / 9KW
INPUT			
Phase	Single Phase		
Rated Voltage	208Vac		
Voltage Range	176Vac-300Vac at 100% load, 110Vac-300Vac at 50% load		
Frequency Range	50 ± 10% or 60 ± 10% Hz		
Power Factor	≥0.99		
Current THDi	≤5%(100% linear load)		
Bypass Voltage Range	208 Vac (Phase Voltage) Upper limit: +10%、+15%、+20%、+25%(default: +15%) Lower limit: -10%、-20%、-30%、-40%(default: -20%) Frequency range: ± 10%		
Generator Input Support			
Output			
Phase	Bi-Phases		
Rated Voltage	208/220/230/240Vac;104*2/110*2/115*2/120*2Vac; 50/60Hz		
Power Factor	0.9		
Voltage Regulation	± 1%		
Frequency	Utility Mode	± 1%、± 2%、± 4%、± 5%、± 10% of the rated frequency(optional)	
	Battery Mode	(50/60 ± 0.2%)Hz	
Crest Factor	3:1(max)		
THD	≤2% with linear load		
	≤5% with non linear load		
Waveform	Pure Sine Wave		
Efficiency			
Efficiency	Utility Mode	≥92.5%	
	Battery Mode	≥80%	
Battery			
Voltage	Long time unit Optional Voltage: ± 96V / ± 108V / ± 120Vdc		
	16 / 18 / 20pcs 12V battery		
Charge Current(A)	Long time unit Maximum current 6A(charge current can be set according to battery capacity installed)		
Transfer Time			
uninterruptible transfer: 0ms			
interrupted transfer: < 15ms (50Hz), < 13.33ms (60Hz)[1]			
Protection			
Overload	AC Mode	Load ≤110%: last 60min , ≤ 125%: last10min , ≤150%: last 1min, ≥150% shut down UPS immediately	100%≤Load≤127%: last 1min;load ≥127%:shut down UPSimmediately
	Bat. Mode	Load ≤ 110%: last 10min , ≤ 125%: last1min, ≤150%: last 5S, ≥ 150% shut down UPS immediately	100% ≤Load : shut down UPS immediately
	Bypass Mode	Breaker 100A	Breaker 125A
Short Circuit	Hold Whole System		
Overheat	Line Mode: Switch to Bypass; Backup Mode:Shut down UPS immediately		
Battery Low	EOD VOLTAGE+0.15V/CELL		
Self-diagnostics	Upon Power On and Software Control		
EPO(optional)	Shut down UPS output immediately		
Battery	Advanced Battery Management		
Noise Suppression	Complies with EN62040-2		
Alarms			
Audible & Visual	Line Failure, Battery Low, Overload, System Fault		
Display			
Status LED & LCD	Line Mode, Bypass Mode, Battery Low, Battery Bad, Overload & UPS Fault		
Reading On the LCD	Input Voltage, Input Frequency, Output Voltage, Output Frequency, Load Percentage, Battery Voltage & Inner Temperature		
Communication Interface			
USB, RS232, Dry Contact (optional)			
Environment			
Operating Temperature	0℃ ~ 40℃		
Storage Temperature	-25℃ ~ 55℃		
Humidity	0 ~ 95% non condensing		
NOISE LEVEL(dB)	<55dB (1 METER)		
Altitude	< 1500m		
Other			
Unit Dimensions (W × D × H)	S Model:810*250*675; H Model:250*502*616		
Weight (Kg)	55/21		58/22
Safety Conformance	CE,EN/IEC 62040-2,EN/IEC 62040-1-1		

Specifications subject to change without prior notice.